



## POWER ANALYZER

- Basic Power Accuracy < 0.005%
- 5A Current Input with 10 Current Ranges
- 240/120V Voltage Input
- Line and Line to Line Voltage Measurements
- Full Power Factor Range
- Distorted Waveforms
- Total Harmonic Distortion Waveforms
- Complete Waveform Analysis
- Phasor Analytical Representation
- Single-Phase / Three-Phase Series of Wattmeter/Power Analyzers

## SERIES OF WATTMETERS/POWER ANALYZERS



2023A SHOWN

## Series of Wattmeter/Power Analyzers

The 2020A/2023A Series is the latest development from Measurements International. They represent a new proprietary sampling method for the precise measurement of electrical power for applications including product efficiency testing, transformer testing and other power conversion products. Developed as a power analyzer in a self-contained standard or in a transformer loss measurement system.

**Customers now have 4 different models to choose from to cover their required application.**

The single phase version Model 2020A is offered in the standard wattmeter version or can be purchased as the 2020A-XP extended performance for full power analyzer applications. It features total harmonic distortion analysis, complete waveform analysis and phasor analytical representation.

**The new 3-phase version Model 2023A** is offered in two different versions also. A 3-phase wattmeter 2023A, or the Model 2023A-XP version power analyzer. The 2023A-XP is a 3-phase power analyzer that has the additional features of total harmonic distortion analysis, complete waveform analysis and phasor analytical representation.

A large touch screen display is used to change the input parameters and for indicating the voltage, current and power measurements simultaneously. Waveforms of the input voltage and current can also be displayed and saved to a USB Stick on the front panel or transferred to a computer over the LAN. An Rs232 interface is standard and an Optional IEEE-GPIB card is available. With the IEEE Card only the Voltage, Current and Power values can be transferred. Waveform data is transferred over the LAN.

The 2020A/2023A can be used to measure line to ground and line to line voltage measurements that are 120° apart with one current input. The current input is a two-stage-compensated current-transformer with 10 current ranges from 5A down to 5 mA, the voltage input consists of an accurate voltage divider with 120V and 240V ranges.

The displayed output for power is expressed as  $VI \cos\phi$ . The measurement high accuracy's is maintained for all power factors. The relative conversion error of the output is linear and does not depend on the magnitude or distortion of the input signals.



## Series of Wattmeter/Power Analyzers

Specifications: Rev 0

Model No.	2020A Single-Phase	2020A-XP Single-Phase	2023A Three-Phase	2023A-XP Three-Phase
Input Channels	2Voltages + 1Current	2Voltages + 1Current	3Voltages + 3Currents	3Voltages + 3Currents
Application	Wattmeter	Power Analyzer	Wattmeter	Power Analyzer
<b>Voltage</b>				
<b>120 Volt</b>	Yes	Yes	Yes	Yes
Accuracy (ppm)	±25	±25	±25	±25
Linearity (ppm)	≤20	≤20	≤20	≤20
Input Impedance (Ω)	500k	500k	500k	500k
Frequency (Hz)	12 to 400	12 to 400	12 to 400	12 to 400
<b>240 Volt</b>	Yes	Yes	Yes	Yes
Accuracy (ppm)	±25	±25	±25	±25
Linearity (ppm)	≤20	≤20	≤20	≤20
Input Impedance (Ω)	1M	1M	1M	1M
Frequency (Hz)	12 to 400	12 to 400	12 to 400	12 to 400
<b>Current Measurement</b>				
Ranges (A)	0.005, 0.01, 0.02, 0.05, 1, 2, 5	0.005, 0.01, 0.02, 0.05, 1, 2, 5	0.005, 0.01, 0.02, 0.05, 1, 2, 5	0.005, 0.01, 0.02, 0.05, 1, 2, 5
Accuracy (ppm)	±25	±25	±25	±25
Linearity (ppm)	≤20	≤20	≤20	≤20
Input Impedance (Ω)	3.5	3.5	3.5	3.5
Isolation (Vpp)	600	600	600	600
Frequency (Hz)	12 to 400	12 to 400	12 to 400	12 to 400





## Series of Wattmeter/Power Analyzers

### Specifications: Rev 0

Model No.	2020A Single Phase		2020A-XP Single Phase		2023A Three Phase		2023A-XP Three Phase	
Input Channels	2 Voltage + 1 Current		2 Voltage + 1 Current		3 Voltage + 3I		3 Voltage + 3I	
Application	Wattmeter		Power Analyzer		Wattmeter		Power Analyzer	
<b>Power Measurement</b>								
Power Factor	0 to 0.5	> 0.5	0 to 0.5	> 0.5	0 to 0.5	> 0.5	0 to 0.5	> 0.5
Line to GND Accuracy (ppm)	±25	±50	±25	±50	±25	±50	±25	±75
Line to Line Accuracy (ppm)	±25	±75	±35	±75	±35	±75	±35	±75
Linearity (ppm)	≤20		≤20		≤20		≤20	
Harmonic Distortions Measurement	No		Yes		No		Yes	
Complete Waveform Analysis	No		Yes		No		Yes	
Phasor Analysis	No		Yes		No		Yes	
<b>Operating Environment</b>								
Temperature (Celcius)	15 to 40		15 to 40		15 to 40		15 to 40	
Relative Humidity	10 to 80 Non		10 to 80 Non Condensing		10 to 80 Non Condensing		10 to 80 Non Condensing	
<b>Line Voltage</b>								
Voltage (V)	100 to 240		100 to 240		100 to 240		100 to 240	
Frequency (Hz)	47 to 63		47 to 63		47 to 63		47 to 63	
<b>Dimensions</b>	480 x 585 x 175 (mm)		480 x 585 x 175 (mm)		480 x 585 x 235 (mm)		480 x 585 x 235 (mm)	
<b>Weight</b>	15 kg		15 kg		28 kg		28 kg	

### Corporate Headquarters

Measurements International  
PO Box 2359, 118 Commerce Drive  
Prescott, Ontario, Canada K0E 1T0

Phone: (613) 925-5934  
Fax: (613) 925-1195  
Email: sales@mintl.com  
Toll Free: 1-800-324-4988

© Copyright 2019 Measurements International Limited.  
All rights reserved.



SEPTIEMBRE, 31 28022 MADRID  
TEL. 913000191  
[www.idm-instrumentos.es](http://www.idm-instrumentos.es)  
[idm@idm-instrumentos.es](mailto:idm@idm-instrumentos.es)



[www.mintl.com](http://www.mintl.com)